



FIRSTLINE PLT 924

THREE PHASE CENTRAL INVERTER FOR EMERGENCY LIGHTING APPLICATIONS

9 - 54 KW

APPLICATIONS INCLUDE

- Theaters/Concert Halls
- Auditoriums
- Worship Facilities
- Conference/Banquet Centers
- Shopping Malls
- Casinos
- Sports Facilities
- University Buildings
- Healthcare Facilities
- Correctional Facilities
- Subway/Train Stations
- Industrial Manufacturing
- Warehouses

PRODUCT FEATURES

- **Compact & Reliable**
Provides for a smaller footprint. Cooler operation extends internal component life.
- **AC Input Performance**
High input power factor of 0.99. Low input current distortion of < 1% (THDi) @ full load. Soft Start Power walk-in function that ensures progressive rectifier start-up





MORE FEATURES

IGBT AND DIGITAL SIGNAL PROCESSOR (DSP)

Reduces the impact of the UPS on the local supply. Simplifies installation where there is limited power capacity.

DUAL INPUT

Main power and secondary bypass standby power increase resilience of single or parallel system configuration.

ADAPTIVE FEED CANCELLATION

Advanced control with AFC forward cancellation technology for low harmonic distortion.

MENU SELECT DISPLAY

User friendly display is easy to see and intuitive to use.

PARALLEL UP TO 4 UNITS

Provides redundancy for mission critical applications with no additional hardware. Parallel Kit, Communication through CANBUS Parallel Card

INSTALLATION SAVINGS

System arrives with batteries pre-mounted and wired saving additional labor cost.

FirstLine® PLT 924 Emergency Lighting System (ELS) delivers high performance, tailored to meet the demands of emergency lighting applications. With a cost-effective reliable design, the FirstLine® PLT 924 helps to ensure personnel safety, during an outage condition. The FirstLine® PLT 924 offers more security and versatility to meet illumination requirements, and is the perfect complement for all lighting applications. Our inverter technology effectively maintains critical equipment with extended brownout protection, tight voltage regulation, and power conditioning. Tight voltage regulation assures that facility egress lumens are maintained 100% at emergency lighting fixtures, in all modes of operation, and also extends ballast, LED driver, and lamp life. FirstLine® PLT 924 features unparalleled quality and reliability, with constant conditioned power to virtually any lighting type. The Staco optional Power Distribution Unit (PDU) makes for a well coordinated circuit distribution system.

BATTERY CARE SYSTEM

FirstLine® P 924 uses the Battery Care System which optimizes battery performance while extending battery life.

FRONT PANEL DISPLAY



WARRANTY

ELECTRONICS

A full Two Year On-site Warranty (Continental U.S., Canada or Mexico)

BATTERY

Three (3) Year Full, Limited Warranty, on the Battery System ensures that your batteries are protected from system failure now and in the future. (Warranty provided by battery manufacturer.) Extended warranties, customized service and preventative maintenance plans are also available. Please refer to our warranty statement for complete details.



FIRSTLINE PLT 924

In the event of an AC power failure, the FirstLine® PLT 924 ELS automatically supports the connected lighting loads on battery power and will continue to provide power without any interruption for the specified backup time. When the utility power returns to normal, FirstLine® PLT 924 ELS will automatically recharge the batteries to be ready for the next power disturbance. In addition to meeting life safety requirements, the FirstLine® PLT 924 Emergency Lighting System can also increase the life expectancy of the protected lighting system and reduce long-term cost of ownership.

TECHNICAL SPECIFICATIONS

GENERAL

- On-line double-conversion topology
- True sine wave output
- Continuous, no-break operation
- Three-phase system will support single or three-phase loads
- LCD front panel monitoring and control
- Automatic system bypass
- Circuit breaker protection integral with battery cabinet, molded-case type
- Available with standard UL924 listing with 90 Minute battery and listed for Auxiliary Lighting and Power Equipment

INPUT

- Input Voltage 208Y/120VAC and 480Y/277VAC, 4-wire and 3-wire Delta connection available
- Input Voltage Range: +15%/-20% from nominal
- Input frequency: 60Hz +/-5%
- Full load walk-in from 25% to 100% of rated load in <5 seconds
- Harmonic current distortion <1% at full load
- Surge Withstand: Meets IEEE C62.41

OUTPUT

- IGBT: true sine wave PWM inverter
- Inverter output distortion: <5% THD (100% non-linear)
- Inverter output distortion: <2% THD (linear loads)
- Voltage regulation: +/-2% of nominal at full load
- Frequency: 60/50 Hz

BATTERY

- Designed for easy maintenance
- Standard backup time of 90 minutes at full load
- Valve-Regulated Lead-Acid (VRLA) battery
- 10 year design life at 77°F (25°C)

HOUSING

- Freestanding, NEMA 1 steel enclosure
- Service access—Front and Left Side
- Bottom access for conduit entries

ENVIRONMENTAL

- Agency Compliance: UL 924 listed as "Emergency Lighting Equipment" and "Auxiliary Lighting and Power Equipment". Complies with NFPA 101 Life Safety Code.
- Operating temperature range 18°F (-8°C) to 104°F (40°C)
- Acoustical Noise: 67 dbA Max. at 3 feet
- Relative Humidity: 0-95% non-condensing
- Seismic certified

MONITORING/COMMUNICATIONS

- Front Panel LCD Display:
 - 3x5" x 4.58"H character display
 - System status and alarms
- Communications Port:
 - RS-232
 - Dry Contacts
 - Remote Monitoring
 - SNMP (Optional) and MODBUS RTU (Standard)

WHAT IS AN EMERGENCY LIGHTING SYSTEM?

The National Fire Protection Association (NFPA) has written Life Safety Code® (NFPA 101®*) that defines the requirements for emergency lighting for means of egress. The standard requires that emergency illumination shall be provided for not less than 1½ hours (90 minutes) in the event of failure of normal lighting. The FirstLine® PLT 924 Centralized Emergency Lighting inverter is UL 924 listed as “Emergency Lighting Equipment” and “Auxiliary Lighting and Power Equipment”, as well as NFPA compliant as “Life Safety Equipment”.

Central lighting inverter system provides for a single point for power connection, monitoring and management of emergency lighting; plus eliminates the high cost of maintenance and testing of each individual emergency light, while security and peace-of-mind is improved. Additionally, other critical loads can be protected such as data security and fire.

* Copies of summaries of these NFPA Codes are available upon request.

FIRSTLINE PLT 924 TECHNICAL SPECIFICATIONS

Electrical Data	ELS Power (kW)						
	10	15	20	30	40	50	60
Input							
Topology	On-Line Double Conversion						
Voltage	208Y/120 VAC, Three Phase, 4 wire plus ground, 208VAC, 3 wire (Delta) or 220Y/127VAC configurable from the front panel 480Y/277 VAC 4 wire plus ground or 480 VAC, 3 wire (Delta)						
Range	+15% / -20% Battery Discharge@-15% with full load						
Frequency	60/50Hz +/- 5.0 Hz						
Power Factor	0.99 at 100% load, 0.98 minimum at 50% load						
Current Distortion (THD)	<1% @100% Load, <2% @ 50% Load, <5% @ 10% Load						
Input Current (A)*	Nominal: 28 Maximum: 33	Nominal: 42 Maximum: 49	Nominal: 55 Maximum: 65	Nominal: 83 Maximum: 97	Nominal: 111 Maximum: 130	Nominal: 143 Maximum: 172	Nominal: 172 Maximum: 206
Input Current Inrush	Walk-In from 25% maximum to 100% full load rating in 5 seconds						
Output							
Voltage	208Y/120 VAC, Three Phase, 4 wire plus ground or 220Y/127 VAC configurable from the Front Panel or 480Y/277 VAC, 4-wire						
Static Voltage Regulation	+/- 2%						
Voltage Transient Response	Voltage transient response shall not exceed the following, and shall recover to 95% within 10 milliseconds: a) < 5% RMS for 100% step load b) +/- 1% (loss or return of AC input)						
Frequency (inverter synchronous)	60/50Hz (tracks frequency of static bypass source) +/- 0.5, 1.0, 2.0, 5.0 Hz (user settable)						
Frequency Slew Rate (inverter synchronized to static bypass)	± 10 Hz per second						
Free Running Frequency (on battery or asynchronous)	60/50Hz +/- 0.01Hz						
Voltage Distortion THD	Less than 1% (Linear load), less than 2% with crest factor						
Inverter Overload	125% for 10 minutes, 150% for 60 seconds						
Bypass Overload	400% for 10 seconds, 1000% for half line cycle						
Bypass Input - Range Synchronization Voltage	+12% / -15%						
Bypass Input Frequency Tracking Range	+/- 5Hz						
Overall Efficiency	Up to 94%						
Output Current (A)*	28	42	55	83	111	139	167
Heat Rejection (BTU/Hr)*	2,400	3,500	4,700	7,000	9,300	21,000	18,300
Battery Run Time (minutes)							
Required Battery Time	90 Minutes @ Full Load						
Environmental							
Altitude	De-rate load capability above 1000 meters, 1% per 100 meters						
Operating Temperature	40 °C Maximum						
Audible Noise @ 3 feet "A" weighted scale	61dBA			<75 dBA			
Communications							
*Typical results for 208V applications	SNMP Card & UPS PowerView Pro Shutdown and Monitoring Software for Windows/Novell						
Modbus	Monitoring & Control via RS-485/RTU Protocol/Read Holding and Write Registers						
Standards							
UL 924 listed as “Emergency Lighting Equipment” and “Auxiliary Lighting and Power Equipment”. Complies with NFPA 101 Life Safety Code.							

FIRSTLINE PLT 924 ELS 9kW,13.5kW & 18kW MODELS

Part Number	kW	Voltage	Description	Dimensions (H" x W" x D")	# Battery Cabinets	Weight (lbs.)
208 X 208						
FLP-924-09T	9	208Y/120 208Y/120	9 kW UL924 System, 208Y/120V input & 208Y/120V output	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6 Battery #1: 51.42 x 26.12 x 35.55 (1306 x 663.6 x 903)	2	2171 (985)
FLP-924-09T-2D-2Y	9	208 208Y/120	9 kW UL924 System, 208V input & 208Y/120V output	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6 Battery #1: 51.42 x 26.12 x 35.55 (1306 x 663.6 x 903)	2	2351 (1067)
480 X 208						
FLP-924-09T-4D-2Y	9	480 208Y/120	9 kW UL924 System, 480V input & 208Y/120V output	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6 Battery #1: 51.42 x 26.12 x 35.55 (1306 x 663.6 x 903)	2	2381 (1080)
FLP-924-09T-4Y-2Y	9	480Y/277 208Y/120	9 kW UL924 System, 480Y/277V input & 208Y/120V output	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6 Battery #1: 51.42 x 26.12 x 35.55 (1306 x 663.6 x 903)	2	2271 (1031)
480 X 480						
FLP-924-09T-4D-4Y	9	480 480Y/277	9 kW UL924 System, 480V input & 480Y/277V output	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6 Battery #1: 51.42 x 26.12 x 35.55 (1306 x 663.6 x 903)	2	2481 (1126)
FLP-924-09T-4Y-4Y	9	480Y/277 480Y/277	9 kW UL924 System, 480Y/277V input & 480Y/277V output	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6 Battery #1: 51.42 x 26.12 x 35.55 (1306 x 663.6 x 903)	2	2371 (1076)
208 X 208						
FLP-924-13T	13.5	208Y/120 208Y/120	13.5 kW UL924 System, 208Y/120V input & 208Y/120V	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6 Battery #1: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3)	2	3189 (1447)
FLP-924-13T-2D-2Y	13.5	208 208Y/120	13.5 kW UL924 System, 208V input & 208Y/120V output	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6 Battery #1: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3)	2	3439 (1560)
480 X 208						
FLP-924-13T-4D-2Y	13.5	480 208Y/120	13.5 kW UL924 System, 480V input & 208Y/120V output	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6 Battery #1: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3)	2	3439 (1560)
FLP-924-13T-4Y-2Y	13.5	480Y/277 208Y/120	13.5 kW UL924 System, 480Y/277V input & 208Y/120V output	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6 Battery #1: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3)	2	3389 (1538)
480 X 480						
FLP-924-13T-4D-4Y	13.5	480 480Y/277	13.5 kW UL924 System, 480V input & 480Y/277V output	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6 Battery #1: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3)	2	3639 (1651)
FLP-924-13T-4Y-4Y	13.5	480Y/277 480Y/277	13.5 kW UL924 System, 480Y/277V input & 480Y/277V output	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6 Battery #1: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3)	2	3589 (1628)
208 X 208						
FLP-924-18T	18	208Y/120 208Y/120	18 kW UL924 System, 208Y/120V input & 208Y/120V output	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6 Battery #1: 78.74 x 40 x 29.5 (2000 x 1016 x 749.3)	2	4089 (1855)
FLP-924-18T-2D-2Y	18	208 208Y/120	208Y/120V output 18 kW UL924 System, 208V input & 208Y/120V output	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6 Battery #1: 78.74 x 40 x 29.5 (2000 x 1016 x 749.3)	2	4319 (1959)
480 X 208						
FLP-924-18T-4D-2Y	18	480 208Y/120	18 kW UL924 System, 480V input & 208Y/120V output	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6 Battery #1: 78.74 x 40 x 29.5 (2000 x 1016 x 749.3)	2	4389 (1991)
FLP-924-18T-4Y-2Y	18	480Y/277 208Y/120	18 kW UL924 System, 480Y/277V input & 208Y/120V output	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6 Battery #1: 78.74 x 40 x 29.5 (2000 x 1016 x 749.3)	2	4319 (1959)
480 X 480						
FLP-924-18T-4D-4Y	18	480 480Y/277	18 kW UL924 System, 480V input & 480Y/277V output	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6 Battery #1: 78.74 x 40 x 29.5 (2000 x 1016 x 749.3)	2	4619 (2095)
FLP-924-18T-4Y-4Y	18	480Y/277 480Y/277	18 kW UL924 System, 480Y/277V input & 480Y/277V output	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6 Battery #1: 78.74 x 40 x 29.5 (2000 x 1016 x 749.3)	2	4549 (2064)

FIRSTLINE PLT 924 ELS 27kW & 36kW MODELS

Part Number	kW	Voltage	Description	Dimensions (H" x W" x D")	# Battery Cabinets	Weight (lbs.)
208 X 208						
FLP-924-27T	27	208Y/120 208Y/120	27 kW UL924 System, 208Y/120V input & 208Y/120V output	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6) Battery #1: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3) Battery #2: 78.74 x 40 x 29.5 (2000 x 1016 x 749.3)	3	6079 (2758)
FLP-924-27T-2D-2Y	27	208 208Y/120	27 kW UL924 System, 208V input & 208Y/120V output	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6) Battery #1: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3) Battery #2: 78.74 x 40 x 29.5 (2000 x 1016 x 749.3)	3	6509 (2953)
480 X 208						
FLP-924-27T-4D-2Y	27	480 208Y/120	27 kW UL924 System, 480V input & 208Y/120V output	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6) Battery #1: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3) Battery #2: 78.74 x 40 x 29.5 (2000 x 1016 x 749.3)	3	6509 (2953)
FLP-924-27T-4Y-2Y	27	480Y/277 208Y/120	27 kW UL924 System, 480Y/277V input & 208Y/120V output	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6) Battery #1: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3) Battery #2: 78.74 x 40 x 29.5 (2000 x 1016 x 749.3)	3	6344 (2878)
480 X 480						
FLP-924-27T-4D-4Y	27	480 480Y/277	27 kW UL924 System, 480V input & 480Y/277V output	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6) Battery #1: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3) Battery #2: 78.74 x 40 x 29.5 (2000 x 1016 x 749.3)	3	6774 (3073)
FLP-924-27T-4Y-4Y	27	480Y/277 480Y/277	27 kW UL924 System, 480Y/277V input & 480Y/277V output	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6) Battery #1: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3) Battery #2: 78.74 x 40 x 29.5 (2000 x 1016 x 749.3)	3	6609 (2998)
208 X 208						
FLP-924-36T	36	208Y/120 208Y/120	36 kW UL924 System, 208Y/120V input & 208Y/120V output	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6) Battery #1: 78.74 x 40 x 29.5 (2000 x 1016 x 749.3) Battery #2: 78.74 x 40 x 29.5 (2000 x 1016 x 749.3)	3	7519 (3411)
FLP-924-36T-2D-2Y	36	208 208Y/120	36 kW UL924 System, 208V input & 208Y/120V output	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6) Battery #1: 78.74 x 40 x 29.5 (2000 x 1016 x 749.3) Battery #2: 78.74 x 40 x 29.5 (2000 x 1016 x 749.3)	3	7953 (3608)
480 X 208						
FLP-924-36T-4D-2Y	36	480 208Y/120	36 kW UL924 System, 480V input & 208Y/120V output	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6) Battery #1: 78.74 x 40 x 29.5 (2000 x 1016 x 749.3) Battery #2: 78.74 x 40 x 29.5 (2000 x 1016 x 749.3)	3	7969 (3615)
FLP-924-36T-4Y-2Y	36	480Y/277 208Y/120	36 kW UL924 System, 480Y/277V input & 208Y/120V output	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6) Battery #1: 78.74 x 40 x 29.5 (2000 x 1016 x 749.3) Battery #2: 78.74 x 40 x 29.5 (2000 x 1016 x 749.3)	3	7789 (3533)
480 X 480						
FLP-924-36T-4D-4Y	36	480 480Y/277	36 kW UL924 System, 480V input & 480Y/277V output	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6) Battery #1: 78.74 x 40 x 29.5 (2000 x 1016 x 749.3) Battery #2: 78.74 x 40 x 29.5 (2000 x 1016 x 749.3)	3	8239 (3738)
FLP-924-36T-4Y-4Y	36	480Y/277 480Y/277	36 kW UL924 System, 480Y/277V input & 480Y/277V output	Electronics: 72.41 x 23.13 x 34.47 (1839.3 x 587.4 x 875.6) Battery #1: 78.74 x 40 x 29.5 (2000 x 1016 x 749.3) Battery #2: 78.74 x 40 x 29.5 (2000 x 1016 x 749.3)	3	8059 (3656)

FIRSTLINE PLT 924 ELS 45kW & 54kW MODELS

Part Number	kW	Voltage	Description	Dimensions (H" x W" x D")	# Battery Cabinets	Weight (lbs.)
208 X 208						
FLP-924-45T	45	208Y/120 208Y/120	45 kW UL924 System, 208Y/120V input & 208Y/120V output	Electronics: 76.79 x 34.25 x 34.34 (1950.5 x 870 x 872.3) Battery #1: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3) Battery #2: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3)	3	9041 (4102)
FLP-924-45T-2D-2Y	45	208 208Y/120	45 kW UL924 System, 208V input & 208Y/120V output	Electronics: 76.79 x 34.25 x 34.34 (1950.5 x 870 x 872.3) Battery #1: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3) Battery #2: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3)	3	9621 (4365)
480 X 208						
FLP-924-45T-4D-2Y	45	480 208Y/120	45 kW UL924 System, 480V input & 208Y/120V output	Electronics: 76.79 x 34.25 x 34.34 (1950.5 x 870 x 872.3) Battery #1: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3) Battery #2: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3)	3	9451 (4288)
FLP-924-45T-4Y-2Y	45	480Y/277 208Y/120	45 kW UL924 System, 480Y/277V input & 208Y/120V output	Electronics: 76.79 x 34.25 x 34.34 (1950.5 x 870 x 872.3) Battery #1: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3) Battery #2: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3)	3	9451 (4288)
480 X 480						
FLP-924-45T-4D-4Y	45	480 480Y/277	45 kW UL924 System, 480V input & 480Y/277V output	Electronics: 76.79 x 34.25 x 34.34 (1950.5 x 870 x 872.3) Battery #1: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3) Battery #2: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3)	3	9861 (4474)
FLP-924-45T-4Y-4Y	45	480Y/277 480Y/277	45 kW UL924 System, 480Y/277V input & 480Y/277V output	Electronics: 76.79 x 34.25 x 34.34 (1950.5 x 870 x 872.3) Battery #1: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3) Battery #2: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3)	3	9861 (4474)
208 X 208						
FLP-924-54T	54	208Y/120 208Y/120	54 kW UL924 System, 208Y/120V input & 208Y/120V output	Electronics: 76.79 x 34.25 x 34.34 (1950.5 x 870 x 872.3) Battery #1: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3) Battery #2: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3)	3	9041 (4102)
FLP-924-54T-2D-2Y	54	208 208Y/120	54 kW UL924 System, 208V input & 208Y/120V output	Electronics: 76.79 x 34.25 x 34.34 (1950.5 x 870 x 872.3) Battery #1: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3) Battery #2: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3)	3	9599 (4355)
480 X 208						
FLP-924-54T-4D-2Y	54	480 208Y/120	54 kW UL924 System, 480V input & 208Y/120V output	Electronics: 76.79 x 34.25 x 34.34 (1950.5 x 870 x 872.3) Battery #1: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3) Battery #2: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3)	3	9601 (4356)
FLP-924-54T-4Y-2Y	54	480Y/277 208Y/120	54 kW UL924 System, 480Y/277V input & 208Y/120V output	Electronics: 76.79 x 34.25 x 34.34 (1950.5 x 870 x 872.3) Battery #1: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3) Battery #2: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3)	3	9607 (4358)
480 X 480						
FLP-924-54T-4D-4Y	54	480 480Y/277	54 kW UL924 System, 480V input & 480Y/277V output	Electronics: 76.79 x 34.25 x 34.34 (1950.5 x 870 x 872.3) Battery #1: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3) Battery #2: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3)	3	10167 (4612)
FLP-924-54T-4Y-4Y	54	480Y/277 480Y/277	54 kW UL924 System, 480Y/277V input & 480Y/277V output	Electronics: 76.79 x 34.25 x 34.34 (1950.5 x 870 x 872.3) Battery #1: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3) Battery #2: 78.74 x 36 x 29.5 (2000 x 914.4 x 749.3)	3	10173 (4615)

LIGHTING TYPES SUPPORTED:

- Light Emitting Diode (LED) Lighting
- Incandescent
- Magnetic and electronic fluorescent ballasts
- High power factor compact fluorescent
- High Intensity Discharge (HID)
- High Pressure Sodium (HPS)
- Metal Halide (MH)

CENTRAL INVERTER SYSTEM ADVANTAGES

- Single point operations for simplified testing and record keeping
- Simplified service for reduced cost of ownership
- Industry standard battery pack for easy maintenance

STACO SERVICE

FIELD SERVICE PROGRAM

Staco specializes in providing choice and flexibility by developing tailored solutions for preventive and remedial maintenance services, as well as emergency repairs for all of our products. Staco Service is built upon a nationwide network of highly trained and motivated customer support engineers and technicians who can provide professional services and care throughout the life of your equipment.

- Start-Ups
- Preventive Maintenance
- Spare Parts
- Battery Analysis/Refresh/Replacement
- On-Site Training
- Time & Material Services

WHY STACO ENERGY PRODUCTS?

BECAUSE WE ARE YOUR CUSTOM POWER SOLUTIONS PROVIDER!

Unique application design demands, harsh environment concerns, the need to meet non-standard physical space requirements; providing the "not so usual" is what we do best. From leading edge uninterruptible power supplies, power conditioners, power factor and harmonic correction equipment, to the world's most stable voltage control systems, we have the technology you need to protect and manage your business, and the knowledge to make it work for you.

Since 1937, customers worldwide have relied on Staco Energy as their custom solutions provider, to solve a wide range of electrical power problems. Headquartered in Miamisburg, Ohio, Staco Energy Products is a wholly owned subsidiary of Components Corporation of America, located in Dallas, Texas.

Voltage Control



UPS & Emergency Lighting



Power Factor & Harmonics



STACO
ENERGY
PRODUCTS CO.

FL-PLT-924_bro-210118

Contact Us:
US Toll Free: 866-261-1191
Phone: 937-253-1191
E-mail: sales@stacoenergy.com